

## APX RADIO QUICK REFERENCE



### Adding Channels to SCAN list:

- Press and hold the **SCAN** button for 2 seconds
- Highlight the channel to add to the **SCAN** list
- Press the **“SEL”** button on the keypad
- **“Z”** will appear and is now in the **SCAN** list
- To remove press **“SEL”** and the **“Z”** will disappear
- 16 channel maximum in SCAN list

**\*Must be utilizing a Trunked Channel to SCAN Trunked Channels**

**\*Must be utilizing a Conventional Channel to SCAN Conventional Channels**

### Adding Channels to Dynamic Zone:

- Dynamic Zone is found by pressing the **“ZnDn”** (Zone Down) on the keypad from **“RED1”**
- Use the 4 arrow keypad to find **“ZnPr”** (Zone Program) – then select it
- Highlight channel position and press **“EDIT”** key
- Highlight **List Selection** and press **“SEL”**
- Select desired zone and press **“SEL”**
- Then select desired channel and press **“SEL”**
- Repeat steps, 16 channel maximum in Dynamic Zone

**\*Note – When changing batteries, ensure (2) clicks are heard when installing new battery**